
Homework I

1. (20%) Considering a DSSS system with BPSK modulation over AWGN channel, the applied spreading code is a purely random code, $PG = 100$ and the received $E_b/N_0 = 0, 1, 2, \dots, 5$ dB.
 - (a) Simulate the BER when the receiver is perfectly synchronized
 - (b) Simulate the BER when $\hat{T}_d - T_d = kT_c/10$, for $k = 1, \dots, 10$
 - (c) Simulate the BER when another purely random code is used at the receiver for despreading.
2. (20%) Repeat Problem 1 for a DSSS system with $PG = 10$. Compare the results with that obtained in Problem 1.
3. (20%) Repeat Problem 1 for an FHSS system with BFSK modulation, $PG = 128$ and one bit is transmitted per hop. (The synchronization error $\hat{T}_d - T_d$ corresponds to the hop duration for FHSS.)
 - Due date: **3/25**, (Submit your report during the class and mail your program to the TA.) Email: TWNTHUCOM5160@gmail.com